

Extension of the frequency-range of interferometers for the "magnetic" components of gravitational waves?

Christian Corda

February 7, 2008

INFN - Sezione di Pisa and Università di Pisa, Via F. Buonarroti 2, I - 56127
PISA, Italy

E-mail address: christian.corda@ego-gw.it

Abstract

Recently, with an enlighting treatment, Baskaran and Grishchuk have shown the presence and importance of the so-called "magnetic" components of gravitational waves (GWs), which have to be taken into account in the context of the total response functions of interferometers for GWs propagating from arbitrary directions. In this paper the analysis of the response functions for the magnetic components is generalized in its full frequency dependence, while in the work of Baskaran and Grishchuk the response functions were computed only in the approximation of wavelength much larger than the linear dimensions of the interferometer. It is also shown that the response functions to the magnetic components grow at high frequencies, differently from the values of the response functions to the well known ordinary components that decrease at high frequencies. Thus the magnetic components could in principle become the dominant part of the signal at high frequencies. This is important for a potential detection of the signal at high frequencies and confirms that the magnetic contributions must be taken into account in the data analysis. More, the fact that the response functions of the magnetic components grow at high frequencies shows that, in principle, the frequency-range of Earth-based interferometers could extend to frequencies over 10000 Hz.

PACS numbers: 04.80.Nn, 04.80.-y, 04.25.Nx

1 Introduction

The design and construction of a number of sensitive detectors for GWs is underway today. There are some laser interferometers like the VIRGO detector, being built in Cascina, near Pisa by a joint Italian-French collaboration [1, 2], the GEO 600 detector, being built in Hanover, Germany by a joint Anglo-Germany collaboration [3, 4], the two LIGO detectors, being built in the United States (one in Hanford, Washington and the other in Livingston, Louisiana) by a joint Caltech-Mit collaboration [5, 6], and the TAMA 300 detector, being built near Tokyo, Japan [7, 8]. There are many bar detectors currently in operation too, and several interferometers and bars are in a phase of planning and proposal stages.

The results of these detectors will have a fundamental impact on astrophysics and gravitation physics. There will be lots of experimental data to be analyzed, and theorists will be forced to interact with lots of experiments and data analysts to extract the physics from the data stream.

Detectors for GWs will also be important to confirm or ruling out the physical consistency of General Relativity or of any other theory of gravitation [9, 10, 11, 12]. This is because, in the context of Extended Theories of Gravity, some differences from General Relativity and the others theories can be seen starting by the linearized theory of gravity [9, 10, 12].

With an enlighting treatment, recently, Baskaran and Grishchuk have shown the presence and importance of the so-called “magnetic” components of GWs, which have to be taken into account in the context of the total response functions (angular patterns) of interferometers for GWs propagating from arbitrary directions [13]. In this paper the analysis of the response functions for the magnetic components is generalized in its full frequency dependence, while in [13] the response functions were computed only in the approximation of wavelength much larger than the linear dimensions of the interferometer (i.e. low frequencies). It is also shown that the response functions to the magnetic components grow at high frequencies, differently from the values of the response functions to the well known ordinary (called “electric” in [13]) components that decrease at high frequencies. Thus the magnetic components could in principle become the dominant part of the signal at high frequencies. This is important for a potential detection of the signal at high frequencies and confirms that the magnetic contributions must be taken into account in the data analysis. More, the fact that the response functions of the magnetic components grow at high frequencies shows that, in principle, the frequency-range of Earth-based interferometers could extend to frequencies over 10000 Hz.

2 Analysis in the frame of the local observer

In a laboratory environment on earth, the coordinate system in which the space-time is locally flat is typically used [12, 13, 14, 15, 16] and the distance between any two points is given simply by the difference in their coordinates in the sense




Figure 1: photons can be launched from the beam-splitter to be bounced back by the mirror

of Newtonian physics. In this frame, called the frame of the local observer, GWs manifest themselves by exerting tidal forces on the masses (the mirror and the beam-splitter in the case of an interferometer, see figure 1).

A detailed analysis of the frame of the local observer is given in ref. [14], sect. 13.6. Here we remember only the more important features of this frame:

- the time coordinate x_0 is the proper time of the observer O;
- spatial axes are centered in O;

in the special case of zero acceleration and zero rotation the spatial coordinates x_j are the proper distances along the axes and the frame of the local observer reduces to a local Lorentz frame: in this case the line element reads

$$ds^2 = (-dx^0)^2 + \delta_{ij}dx^i dx^j + O(|dx^j|^2)dx^\alpha dx^\beta; \quad (1)$$

the effect of GWs on test masses is described by the equation for geodesic deviation in this frame

$$\ddot{x}^i = -\tilde{R}_{0k0}^i x^k, \quad (2)$$

where we have called $\tilde{R}_{0k0}^i$ the linearized Riemann tensor [14].

Recently Baskaran and Grishchuk have shown the presence and importance of the so-called magnetic component of GWs and have computed the detector pattern in the low frequencies approximation [13]. Actually this result can be generalized for all GWs (i.e. not only for ones that have a wavelength much larger than the arms of the interferometer).

Before starting with the analysis of the response functions of interferometers, a brief review of Section 3 of [13] is necessary to understand the importance of the “magnetic” components of GWs. In this paper we use different notations with respect to the ones used in [13]. We work with $G = 1$, $c = 1$ and $\hbar = 1$ and we call $h_+(t_{tt} + z_{tt})$ and $h_\times(t_{tt} + z_{tt})$ the weak perturbations due to the + and the $\times$ polarizations of the GW which are expressed in terms of synchrony

coordinates $t_{tt}, x_{tt}, y_{tt}, z_{tt}$ in the transverse-traceless (TT) gauge. In this way the most general GW propagating in the z_{tt} direction can be written in terms of plane monochromatic waves [14, 15, 16, 17]

$$\begin{aligned} h_{\mu\nu}(t_{tt} + z_{tt}) &= h_+(t_{tt} + z_{tt})e_{\mu\nu}^{(+)} + h_\times(t_{tt} + z_{tt})e_{\mu\nu}^{(\times)} = \\ &= h_{+0} \exp i\omega(t_{tt} + z_{tt})e_{\mu\nu}^{(+)} + h_{\times 0} \exp i\omega(t_{tt} + z_{tt})e_{\mu\nu}^{(\times)}, \end{aligned} \quad (3)$$

and the correspondent line element will be

$$ds^2 = dt_{tt}^2 - dz_{tt}^2 - (1 + h_+)dx_{tt}^2 - (1 - h_+)dy_{tt}^2 - 2h_\times dx_{tt}dx_{tt}. \quad (4)$$

The wordlines $x_{tt}, y_{tt}, z_{tt} = \text{const}$ are timelike geodesics which represent the histories of free test masses [14, 16]. The coordinate transformation $x^\alpha = x^\alpha(x_{tt}^\beta)$ from the TT coordinates to the frame of the local observer is [13, 18]

$$\begin{aligned} t &= t_{tt} + \frac{1}{4}(x_{tt}^2 - y_{tt}^2)\dot{h}_+ - \frac{1}{2}x_{tt}y_{tt}\dot{h}_\times \\ x &= x_{tt} + \frac{1}{2}x_{tt}\dot{h}_+ - \frac{1}{2}y_{tt}\dot{h}_\times + \frac{1}{2}x_{tt}z_{tt}\dot{h}_+ - \frac{1}{2}y_{tt}z_{tt}\dot{h}_\times \\ y &= y_{tt} + \frac{1}{2}y_{tt}\dot{h}_+ - \frac{1}{2}x_{tt}\dot{h}_\times + \frac{1}{2}y_{tt}z_{tt}\dot{h}_+ - \frac{1}{2}x_{tt}z_{tt}\dot{h}_\times \\ z &= z_{tt} - \frac{1}{4}(x_{tt}^2 - y_{tt}^2)\dot{h}_+ + \frac{1}{2}x_{tt}y_{tt}\dot{h}_\times. \end{aligned} \quad (5)$$

In eqs. (5) it is $\dot{h}_+ \equiv \frac{\partial h_+}{\partial t}$ and $\dot{h}_\times \equiv \frac{\partial h_\times}{\partial t}$. We emphasize that, in refs. [13, 18] it has been shown that the linear and quadratics terms, as powers of x_{tt}^α , are unambiguously determined by the conditions of the frame of the local observer.

Considering a free mass riding on a timelike geodesic ($x = l_1, y = l_2, z = l_3$) [13] eqs. (5) define the motion of this mass with respect the introduced frame of the local observer. It is

$$\begin{aligned} x(t+z) &= l_1 + \frac{1}{2}[l_1\dot{h}_+(t+z) - l_2\dot{h}_\times(t+z)] + \frac{1}{2}l_1l_3\dot{h}_+(t+z) + \frac{1}{2}l_2l_3\dot{h}_\times(t+z) \\ y(t+z) &= l_2 - \frac{1}{2}[l_2\dot{h}_+(t+z) + l_1\dot{h}_\times(t+z)] - \frac{1}{2}l_2l_3\dot{h}_+(t+z) + \frac{1}{2}l_1l_3\dot{h}_\times(t+z) \\ z(t+z) &= l_3 - \frac{1}{4}(l_1^2 - l_2^2)\dot{h}_+(t+z) + 2l_1l_2\dot{h}_\times(t+z), \end{aligned} \quad (6)$$

which are exactly eqs. (13) of [13] rewritten using our notation. In absence of GWs the position of the mass is (l_1, l_2, l_3) . The effect of the GW is to drive the mass to have oscillations. Thus, in general, from eqs. (6) all three components of motion are present [13].

Neglecting the terms with $\dot{h}_+$ and $\dot{h}_\times$ in eqs. (6) the “traditional” equations

for the mass motion are obtained [14, 16, 17]

$$\begin{aligned}
x(t+z) &= l_1 + \frac{1}{2}[l_1 h_+(t+z) - l_2 h_\times(t+z)] \\
y(t+z) &= l_2 - \frac{1}{2}[l_2 h_+(t+z) + l_1 h_\times(t+z)] \\
z(t+z) &= l_3.
\end{aligned} \tag{7}$$

Clearly, this is the analogue of the electric component of motion in electrodynamics [13], while equations

$$\begin{aligned}
x(t+z) &= l_1 + \frac{1}{2}l_1 l_3 \dot{h}_+(t+z) + \frac{1}{2}l_2 l_3 \dot{h}_\times(t+z) \\
y(t+z) &= l_2 - \frac{1}{2}l_2 l_3 \dot{h}_+(t+z) + \frac{1}{2}l_1 l_3 \dot{h}_\times(t+z) \\
z(t+z) &= l_3 - \frac{1}{4}(l_1^2 - l_2^2) \dot{h}_+(t+z) + 2l_1 l_2 \dot{h}_\times(t+z),
\end{aligned} \tag{8}$$

are the analogue of the magnetic component of motion. One could think that the presence of these magnetic components is a “frame artefact” due to the transformation (5), but it has to be emphasized that in Section 4 of [13] eqs. (6) have been obtained directly by the geodesic deviation equation too, thus the magnetic components have a really physical significance. The fundamental point of [13] is that the magnetic component becomes important when the frequency of the wave increases, like it is shown in Section 3 of [13]. This can be understood directly from eqs. (6). In fact, using eqs. (3) and eqs. (5), eqs. (6) become

$$\begin{aligned}
x(t+z) &= l_1 + \frac{1}{2}[l_1 h_+(t+z) - l_2 h_\times(t+z)] + \frac{1}{2}l_1 l_3 \omega h_+(t+z) + \frac{1}{2}l_2 l_3 \omega h_\times(t+z) \\
y(t+z) &= l_2 - \frac{1}{2}[l_2 h_+(t+z) + l_1 h_\times(t+z)] - \frac{1}{2}l_2 l_3 \omega h_+(t+z) + \frac{1}{2}l_1 l_3 \omega h_\times(t+z) \\
z(t+z) &= l_3 - \frac{1}{4}(l_1^2 - l_2^2) \omega h_+(t+z) + 2l_1 l_2 \omega h_\times(t+z).
\end{aligned} \tag{9}$$

This also means that the terms with $\dot{h}_+$ and $\dot{h}_\times$ in eqs. (6) can be neglected only when the wavelength goes to infinity [13].

To compute the total response functions of interferometers for the magnetic components generalized in their full frequency dependence, we will use an analysis parallel to the one used for the first time in [15]: the so called “bouncing photon method”. We emphasize that this method has been generalized to scalar waves, angular dependence and massive modes of GWs in [12]. We will see that, in the frame of the local observer, we have to consider two different effects in the calculation of the variation of the round-trip time for photons, in analogy with the cases of refs. [12, 15] where the effects considered were three, but the third effect vanishes putting the origin of our coordinate system in the beam splitter of our interferometer (see also the massive case in [12]). Equations (6), that represent the coordinates of the mirror of the interferometer in presence of a GW in the frame of the local observer, can be rewritten for the pure magnetic component of the + polarization as

$$\begin{aligned}
x(t+z) &= l_1 + \frac{1}{2}l_1l_3\dot{h}_+(t+z) \\
y(t+z) &= l_2 - \frac{1}{2}l_2l_3\dot{h}_+(t+z) \\
z(t+z) &= l_3 - \frac{1}{4}(l_1^2 - l_2^2)\dot{h}_+(t+z),
\end{aligned} \tag{10}$$

where l_1, l_2 and l_3 are the unperturbed coordinates of the mirror.

To compute the response functions for an arbitrary incoming direction of the GW we have to remember that the arms of our interferometer are in the $\vec{u}$ and $\vec{v}$ directions, while the x, y, z frame is the frame of the local observer in phase with the frame of the propagating GW. Then we have to make a spatial rotation of our coordinate system:

$$\begin{aligned}
u &= -x \cos \theta \cos \phi + y \sin \phi + z \sin \theta \cos \phi \\
v &= -x \cos \theta \sin \phi - y \cos \phi + z \sin \theta \sin \phi \\
w &= x \sin \theta + z \cos \theta,
\end{aligned} \tag{11}$$

or, in terms of the x, y, z frame:

$$\begin{aligned}
x &= -u \cos \theta \cos \phi - v \cos \theta \sin \phi + w \sin \theta \\
y &= u \sin \phi - v \cos \phi \\
z &= u \sin \theta \cos \phi + v \sin \theta \sin \phi + w \cos \theta.
\end{aligned} \tag{12}$$

In this way the GW is propagating from an arbitrary direction $\vec{r}$ to the interferometer (see figure 2). Because the mirror of eqs. (10) is situated in the u direction, using eqs. (10), (11) and (12) the u coordinate of the mirror is given by

$$u = L + \frac{1}{4}L^2 A \dot{h}_+(t + u \sin \theta \cos \phi). \tag{13}$$

where we have defined

$$A \equiv \sin \theta \cos \phi (\cos^2 \theta \cos^2 \phi - \sin^2 \phi), \tag{14}$$

and $L = \sqrt{l_1^2 + l_2^2 + l_3^2}$ is the length of the arms of the interferometer.

A good way to analyze variations in the proper distance (time) is by means of “bouncing photons” (see refs. [12, 15] and figure 1).

We start by considering a photon which propagates in the u axis, but we will see in Section 4 that the analysis is almost the same for a photon which propagates in the v axis.

Putting the origin of our coordinate system in the beam splitter of our interferometer and using eq. (13) the unperturbed coordinates for the beam-splitter and the mirror are $u_b = 0$ and $u_m = L$. Thus the unperturbed propagation time between the two masses is




Figure 2: a GW incoming from an arbitrary direction

$$T = L. \quad (15)$$

From eq. (13) we find that the displacements of the two masses under the influence of the GW are

$$\delta u_b(t) = 0 \quad (16)$$

and

$$\delta u_m(t) = \frac{1}{4}L^2 A \dot{h}_+(t + L \sin \theta \cos \phi). \quad (17)$$

In this way, the relative displacement, which is defined by

$$\delta L(t) = \delta u_m(t) - \delta u_b(t) \quad (18)$$

gives

$$\frac{\delta L(t)}{L} = \frac{\delta u_m(t)}{L} = \frac{1}{4}L A \dot{h}_+(t + L \sin \theta \cos \phi). \quad (19)$$

But we have the problem that, for a large separation between the test masses (in the case of Virgo the distance between the beam-splitter and the mirror is three kilometers, four in the case of LIGO), the definition (18) for relative displacements becomes unphysical because the two test masses are taken at the same time and therefore cannot be in a casual connection [12, 15]. We can write the correct definitions for our bouncing photon like

$$\delta L_1(t) = \delta u_m(t) - \delta u_b(t - T_1) \quad (20)$$

and

$$\delta L_2(t) = \delta u_m(t - T_2) - \delta u_b(t), \quad (21)$$

where T_1 and T_2 are the photon propagation times for the forward and return trip correspondingly. According to the new definitions, the displacement of one test mass is compared with the displacement of the other at a later time to allow for finite delay from the light propagation. We note that the propagation times T_1 and T_2 in eqs. (20) and (21) can be replaced with the nominal value T because the test mass displacements are already first order in h_+ [12, 15]. Thus, for the total change in the distance between the beam splitter and the mirror in one round-trip of the photon, we get

$$\delta L_{r.t.}(t) = \delta L_1(t - T) + \delta L_2(t) = 2\delta u_m(t - T) - \delta u_b(t) - \delta u_b(t - 2T), \quad (22)$$

and in terms of the amplitude of the GW:

$$\delta L_{r.t.}(t) = \frac{1}{2}L^2 A \dot{h}_+(t + L \sin \theta \cos \phi - L). \quad (23)$$

The change in distance (23) lead to changes in the round-trip time for photons propagating between the beam-splitter and the mirror:

$$\frac{\delta_1 T(t)}{T} = \frac{1}{2} L A \dot{h}_+(t + L \sin \theta \cos \phi - L). \quad (24)$$

3 Effect of curved spacetime

In the last calculation (variations in the photon round-trip time which come from the motion of the test masses inducted by the magnetic component of the $+$ polarization of the GW), we implicitly assumed that the propagation of the photon between the beam-splitter and the mirror of our interferometer is uniform as if it were moving in a flat space-time. But the presence of the tidal forces indicates that the space-time is curved. As a result we have to consider one more effect after the first discussed that requires spacial separation [12, 15].

From equation (17) we get the tidal acceleration of a test mass caused by the magnetic component of the $+$ polarization of the GW in the u direction

$$\ddot{u}(t + u \sin \theta \cos \phi) = \frac{1}{4} L^2 A \frac{\partial}{\partial t} \ddot{h}_+(t + u \sin \theta \cos \phi). \quad (25)$$

Equivalently we can say that there is a gravitational potential [12, 15]:

$$V(u, t) = -\frac{1}{4} L^2 A \int_0^u \frac{\partial}{\partial t} \ddot{h}_+(t + l \sin \theta \cos \phi) dl, \quad (26)$$

which generates the tidal forces, and that the motion of the test mass is governed by the Newtonian equation

$$\ddot{\vec{r}} = -\nabla V. \quad (27)$$

For the second effect we consider the interval for photons propagating along the u -axis

$$ds^2 = g_{00} dt^2 + du^2. \quad (28)$$

The condition for a null trajectory ($ds = 0$) gives the coordinate velocity of the photons

$$v^2 \equiv \left(\frac{du}{dt}\right)^2 = 1 + 2V(t, u), \quad (29)$$

which to first order in h_+ is approximated by

$$v \approx \pm[1 + V(t, u)], \quad (30)$$

with $+$ and $-$ for the forward and return trip respectively. If we know the coordinate velocity of the photon, we can define the propagation time for its travelling between the beam-splitter and the mirror:

$$T_1(t) = \int_{u_b(t-T_1)}^{u_m(t)} \frac{du}{v} \quad (31)$$

and

$$T_2(t) = \int_{u_m(t-T_2)}^{u_b(t)} \frac{(-du)}{v}. \quad (32)$$

The calculations of these integrals would be complicated because the u_m boundaries of them are changing with time:

$$u_b(t) = 0 \quad (33)$$

and

$$u_m(t) = L + \delta u_m(t). \quad (34)$$

But we note that, to first order in h_+ , these contributions can be approximated by $\delta L_1(t)$ and $\delta L_2(t)$ (see eqs. (20) and (21)). Thus, the combined effect of the varying boundaries is given by $\delta_1 T(t)$ in eq. (24). Then we have only to calculate the times for photon propagation between the fixed boundaries: 0 and L . We will denote such propagation times with $\Delta T_{1,2}$ to distinguish from $T_{1,2}$. In the forward trip, the propagation time between the fixed limits is

$$\Delta T_1(t) = \int_0^L \frac{du}{v(t', u)} \approx L - \int_0^L V(t', u) du, \quad (35)$$

where t' is the retardation time (i.e. t is the time at which the photon arrives in the position L , so $L - u = t - t'$) which corresponds to the unperturbed photon trajectory:

$$t' = t - (L - u).$$

Similiary, the propagation time in the return trip is

$$\Delta T_2(t) = L - \int_L^0 V(t', u) du, \quad (36)$$

where now the retardation time is given by

$$t' = t - u.$$

The sum of $\Delta T_1(t - T)$ and $\Delta T_2(t)$ give us the round-trip time for photons traveling between the fixed boundaries. Then we obtain the deviation of this round-trip time (distance) from its unperturbed value $2T$ as

$$\begin{aligned} \delta_2 T(t) = & - \int_0^L [V(t - 2L + u, u) du + \\ & - \int_L^0 V(t - u, u)] du, \end{aligned} \quad (37)$$

and, using eq. (26), it is

$$\begin{aligned}\delta_2 T(t) = & \frac{1}{4} L^2 A \int_0^L [\int_0^u \frac{\partial}{\partial t} \ddot{h}_+(t - 2T + l(1 + \sin \theta \cos \phi)) dl + \\ & - \int_0^u \frac{\partial}{\partial t} \ddot{h}_+(t - l(1 - \sin \theta \cos \phi)) dl] du.\end{aligned}\quad (38)$$

Thus we have for the total round-trip proper distance in presence of the magnetic component of the + polarization of the GW:

$$T_t = 2T + \delta_1 T + \delta_2 T, \quad (39)$$

and

$$\delta T_u = T_t - 2T = \delta_1 T + \delta_2 T \quad (40)$$

is the total variation of the proper time (distance) for the round-trip of the photon in presence of the GW in the u direction.

Using eqs. (24), (38) and the Fourier transform of h_+ defined by

$$\tilde{h}_+(\omega) = \int_{-\infty}^{\infty} dt h_+(t) \exp(i\omega t), \quad (41)$$

the quantity (40) can be computed in the frequency domain as

$$\tilde{\delta T}_u(\omega) = \tilde{\delta}_1 T(\omega) + \tilde{\delta}_2 T(\omega) \quad (42)$$

where

$$\tilde{\delta}_1 T(\omega) = -i\omega \exp[i\omega L(1 - \sin \theta \cos \phi)] \frac{L^2 A}{2} \tilde{h}_+(\omega) \quad (43)$$

$$\begin{aligned}\tilde{\delta}_2 T(\omega) = & \frac{i\omega L^2 A}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \cos \phi)] - iL\omega(1 - \sin \theta \cos \phi)}{(1 - \sin \theta \cos \phi)^2} + \right. \\ & \left. + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \cos \phi)] - iL\omega(1 + \sin \theta \cos \phi))}{(-1 - \sin \theta \cos \phi)^2} \right] \tilde{h}_+(\omega).\end{aligned}\quad (44)$$

In the above computation the derivation and translation theorems of the Fourier transform have been used. In this way we obtain the response function of the u arm of our interferometer to the magnetic component of the + polarization of the GW as

$$\begin{aligned}H_u^+(\omega) & \equiv \frac{\tilde{\delta T}_u(\omega)}{L\tilde{h}_+(\omega)} = \\ & = -i\omega \exp[i\omega L(1 - \sin \theta \cos \phi)] \frac{LA}{2} + \\ & \quad \frac{i\omega LA}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \cos \phi)] - iL\omega(1 - \sin \theta \cos \phi)}{(1 - \sin \theta \cos \phi)^2} + \right. \\ & \quad \left. + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \cos \phi)] - iL\omega(1 + \sin \theta \cos \phi))}{(-1 - \sin \theta \cos \phi)^2} \right].\end{aligned}\quad (45)$$

4 Computation for the v arm

The computation for the v arm is parallel to the one above. Using eqs. (10), (11) and (12) the coordinate of the mirror in the v arm is:

$$v = L + \frac{1}{4}L^2B\dot{h}_+(t + v \sin \theta \sin \phi), \quad (46)$$

where we have defined

$$B \equiv \sin \theta \sin \phi (\cos^2 \theta \cos^2 \phi - \sin^2 \phi). \quad (47)$$

Thus, with the same way of thinking of previous Sections, we get variations in the photon round-trip time which come from the motion of the beam-splitter and the mirror in the v direction:

$$\frac{\delta_1 T(t)}{T} = \frac{1}{2}LB\dot{h}_+(t + L \sin \theta \sin \phi - L), \quad (48)$$

while the second contribute (propagation in a curve spacetime) will be

$$\begin{aligned} \delta_2 T(t) = & \frac{1}{4}L^2B \int_0^L [\int_0^u \frac{\partial}{\partial t} \ddot{h}_+(t - 2T + l(1 - \sin \theta \sin \phi))dl + \\ & - \int_0^u \frac{\partial}{\partial t} \ddot{h}_+(t - l(1 - \sin \theta \sin \phi))dl] du, \end{aligned} \quad (49)$$

and the total response function of the v arm for the magnetic component of the $+$ polarization of GWs is given by

$$\begin{aligned} H_v^+(\omega) & \equiv \frac{\delta T_u(\omega)}{Lh_+(\omega)} = \\ & = -i\omega \exp[i\omega L(1 - \sin \theta \sin \phi)] \frac{LB}{2} + \\ & + \frac{i\omega LB}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \sin \phi)] - iL\omega(1 - \sin \theta \sin \phi)}{(1 - \sin \theta \cos \phi)^2} + \right. \\ & \left. + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \sin \phi)] - iL\omega(1 + \sin \theta \sin \phi))}{(-1 - \sin \theta \sin \phi)^2} \right]. \end{aligned} \quad (50)$$

5 The total response function of an interferometer for the $+$ polarization

The total response function for the magnetic component of the $+$ polarization is given by the difference of the two response function of the two arms:

$$H_{tot}^+(\omega) \equiv H_u^+(\omega) - H_v^+(\omega), \quad (51)$$

and using eqs. (45) and (50) we obtain a complicated formula

$$\begin{aligned}
H_{tot}^+(\omega) &= \frac{\tilde{\delta}T_{tot}(\omega)}{Lh_+(\omega)} = \\
&= -i\omega \exp[i\omega L(1 - \sin \theta \cos \phi)] \frac{LA}{2} + \frac{LB}{2} i\omega \exp[i\omega L(1 - \sin \theta \sin \phi)] \\
&\quad - \frac{i\omega LA}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \cos \phi)] - iL\omega(1 - \sin \theta \cos \phi)}{(1 - \sin \theta \cos \phi)^2} \right. \\
&\quad + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \cos \phi)] - iL\omega(1 + \sin \theta \cos \phi))}{(-1 - \sin \theta \cos \phi)^2} \left. + \right. \\
&\quad + \frac{i\omega LB}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \sin \phi)] - iL\omega(1 - \sin \theta \sin \phi)}{(1 - \sin \theta \sin \phi)^2} \right. \\
&\quad + \left. \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \sin \phi)] - iL\omega(1 + \sin \theta \sin \phi))}{(-1 - \sin \theta \sin \phi)^2} \right],
\end{aligned} \tag{52}$$

that, in the low frequencies limit is in perfect agreement with the result of Baskaran and Grishchuk (eq. 49 of [13]):

$$H_{tot}^+(\omega \rightarrow 0) = \frac{1}{4} \sin \theta \left[(\cos^2 \theta + \sin 2\phi \frac{1 + \cos^2 \theta}{2}) \right] (\cos \phi - \sin \phi). \tag{53}$$

We emphasize that in our work the x, y, z frame is the frame of the local observer in phase with respect the propagating GW, while in [13] the two frames are not in phase (i.e. in our work the third angle is put equal to zero, this is not a restriction as it is known in literature, see for example [12]).

In figures 3 and 4 the absolute value of the total response functions (52) of the Virgo and LIGO interferometers to the magnetic component of the $+$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ are respectively shown. This value grows at high frequencies. In figure 5 the angular dependence of the total response function (52) of the Virgo and LIGO interferometers to the magnetic component of the $+$ polarization of GWs for $f = 100Hz$ is shown.

6 Analysis for the $\times$ polarization

The analysis can be generalized for the magnetic component of the $\times$ polarization too. In this case, equations (6) can be rewritten for the pure magnetic component of the $\times$ polarization as

$$\begin{aligned}
x(t+z) &= l_1 + \frac{1}{2} l_2 l_3 \dot{h}_\times(t+z) \\
y(t+z) &= l_2 + \frac{1}{2} l_1 l_3 \dot{h}_\times(t+z) \\
z(t+z) &= l_3 - \frac{1}{2} l_1 l_2 \dot{h}_\times(t+z).
\end{aligned} \tag{54}$$

Using eqs. (54), (11) and (12) the u coordinate of the mirror situated in the u arm of the interferometer is given by

$$u = L + \frac{1}{4} L^2 C \dot{h}_\times(t + u \sin \theta \cos \phi). \tag{55}$$




Figure 3: the absolute value of the total response function of the Virgo interferometer to the magnetic component of the + polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$




Figure 4: the absolute value of the total response function of the LIGO interferometer to the magnetic component of the + polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$




Figure 5: the angular dependence of the total response function of the Virgo and LIGO interferometers to the magnetic component of the $+$ polarization of GWs for $f = 100Hz$

where we have defined

$$C \equiv -2 \cos \theta \cos^2 \phi \sin \theta \sin \phi, \quad (56)$$

while the v coordinate of the mirror situated in the v arm of the interferometer is given by

$$v = L + \frac{1}{4} L^2 D \dot{h}_\times(t + v \sin \theta \sin \phi). \quad (57)$$

where it is

$$D \equiv 2 \cos \theta \cos \phi \sin \theta \sin^2 \phi. \quad (58)$$

Thus, with an analysis parallel to the one of previous Sections, it is possible to show that the total response function of the interferometer for the magnetic component of the $\times$ polarization of GWs is

$$\begin{aligned} H_{tot}^\times(\omega) &= \frac{\tilde{\delta T}_{tot}(\omega)}{L \dot{h}_\times(\omega)} = \\ &= -i\omega \exp[i\omega L(1 - \sin \theta \cos \phi)] \frac{LC}{2} + \frac{LD}{2} i\omega \exp[i\omega L(1 - \sin \theta \sin \phi)] \\ &\quad - \frac{i\omega LC}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \cos \phi)] - iL\omega(1 - \sin \theta \cos \phi)}{(1 - \sin \theta \cos \phi)^2} \right. \\ &\quad + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \cos \phi)] - iL\omega(1 + \sin \theta \cos \phi))}{(-1 - \sin \theta \cos \phi)^2} \left. + \right. \\ &\quad + \frac{i\omega LD}{4} \left[\frac{-1 + \exp[i\omega L(1 - \sin \theta \sin \phi)] - iL\omega(1 - \sin \theta \sin \phi)}{(1 - \sin \theta \sin \phi)^2} + \right. \\ &\quad \left. + \frac{\exp(2i\omega L)(1 - \exp[i\omega L(-1 - \sin \theta \sin \phi)] - iL\omega(1 + \sin \theta \sin \phi))}{(-1 - \sin \theta \sin \phi)^2} \right], \end{aligned} \quad (59)$$

that, in the low frequencies limit is in perfect agreement with the result of Baskaran and Grishchuk (eq. 50 of [13]):

$$H_{tot}^\times(\omega \rightarrow 0) = \frac{1}{4} \sin 2\phi (\cos \phi + \sin \phi) \cos \theta. \quad (60)$$

In figure 6 and 7 the absolute value of the total response functions (59) of the Virgo and LIGO interferometers to the magnetic component of the $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ are respectively shown. This value grows at high frequencies in analogy with the case seen in previous Section for the magnetic component of the $+$ polarization. In figure 8 the angular dependence of the total response function (59) of the Virgo and LIGO interferometers to the magnetic component of the $\times$ polarization of GWs for $f = 100Hz$ is shown.

7 Extension of the frequency-range for Earth-based interferometers?

The fact that the values of the response functions of interferometers to the “electric” components (i.e. the well known ordinary components) decrease with




Figure 6: the absolute value of the total response function of the Virgo interferometer to the magnetic component of the $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$




Figure 7: the absolute value of the total response function of the LIGO interferometer to the magnetic component of the $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$




Figure 8: the angular dependence of the total response function of the Virgo and LIGO interferometers to the magnetic component of the $\times$ polarization of GWs for $f = 100Hz$

frequency is well known in literature. This is because the response functions to the electric components are proportional to the function

$$\text{sinc}(\omega L) \equiv \frac{\sin \omega L}{\omega L}, \quad (61)$$

see for example equation 12 of [15] and equation 2.23 of [19]. Then, because the response functions to the “magnetic” components grow with frequency, as it is shown in eqs. (52) and (59) and in their graphics of figures 3,4, 6 and 7, the part of signal which arises from the magnetic components could in principle become the dominant part of the signal at high frequencies (the fact that the response functions to the magnetic components grow with frequency is due to eqs. (9) which show that the motion of test masses is proportional to the frequency). This is important for a potential detection of the signal at high frequencies and confirms the result of [13] that the magnetic contributions must be taken into account in the data analysis in addition of the response functions of the electric components which are well known in literature (see for example [19, 20, 21, 22]). The fact that the response functions of the magnetic components grow at high frequencies also shows that, in principle, the frequency-range of Earth-based interferometers could extend to frequencies over 10000 Hz. In figures 9,10 and 11,12 the absolute value of the total response functions (52) and (59) of the Virgo and LIGO interferometers to the magnetic components of the $+$ and $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ are extended to the range $10000\text{Hz} \leq f \leq 20000\text{Hz}$.

8 Conclusion remarks

The analysis of the response functions of interferometers for the “magnetic” components of GWs has been generalized in its full frequency dependence, while in the work of Baskaran and Grishchuk [13] the response functions were computed only in the low frequencies approximation (i.e. wavelength much larger than the linear dimensions of the interferometer). It has also been shown that the response functions to the magnetic components of GWs grows at high frequencies, thus, because the value of the response functions to the “electric” components (i.e. the well known ordinary components) decreases, the response functions to the magnetic components could in principle begin the dominant part of the signal at high frequencies. This could be important in the context of a detection of the signal at high frequencies and confirms the result of Baskaran and Grishchuk that the magnetic contributions must be taken into account in the data analysis. We also emphasize that the fact that the response functions of the magnetic components grow at high frequencies shows that, in principle, the frequency-range of Earth-based interferometers could extend to frequencies over 10000 Hz.




Figure 9: the absolute value of the total response function of the Virgo interferometer to the magnetic component of the $+$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ in the frequency-range $10000Hz \leq f \leq 20000Hz$




Figure 10: the absolute value of the total response function of the LIGO interferometer to the magnetic component of the + polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ in the frequency-range $10000Hz \leq f \leq 20000Hz$




Figure 11: the absolute value of the total response function of the Virgo interferometer to the magnetic component of the $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ in the frequency-range $10000Hz \leq f \leq 20000Hz$




Figure 12: the absolute value of the total response function of the LIGO interferometer to the magnetic component of the $\times$ polarization of GWs for $\theta = \frac{\pi}{4}$ and $\phi = \frac{\pi}{3}$ in the frequency-range $10000\text{Hz} \leq f \leq 20000\text{Hz}$

Acknowledgements

I would like to thank Maria Felicia De Laurentis and Giancarlo Cella for helpful advices during my work. The European Gravitational Observatory (EGO) consortium has also to be thanked for the using of computing facilities.

References

- [1] Acernese F et al. (the Virgo Collaboration) - Class. Quant. Grav. **23** 19 S635-S642 (2006)
- [2] Acernese F et al. (the Virgo Collaboration) - Class. Quant. Grav. **23** 8 S63-S69 (2006)
- [3] Hild S (for the LIGO Scientific Collaboration) - Class. Quant. Grav. **23** 19 S643-S651 (2006)
- [4] Willke B et al. - Class. Quant. Grav. **23** 8S207-S214 (2006)
- [5] Sigg D (for the LIGO Scientific Collaboration) - www.ligo.org/pdf_public/P050036.pdf
- [6] Abbott B et al. (the LIGO Scientific Collaboration) - Phys. Rev. D **72**, 042002 (2005)
- [7] Ando M and the TAMA Collaboration - Class. Quant. Grav. **19** 7 1615-1621 (2002)
- [8] Tatsumi D, Tsunesada Y and the TAMA Collaboration - Class. Quant. Grav. **21** 5 S451-S456 (2004)
- [9] Capozziello S - *Newtonian Limit of Extended Theories of Gravity* in *Quantum Gravity Research Trends* Ed. A. Reimer, pp. 227-276 Nova Science Publishers Inc., NY (2005) - also in arXiv:gr-qc/0412088 (2004)
- [10] Capozziello S and Troisi A - Phys. Rev. D **72** 044022 (2005)
- [11] Will C M *Theory and Experiments in Gravitational Physics*, Cambridge Univ. Press Cambridge (1993)
- [12] Capozziello S and Corda C - Int. J. Mod. Phys. D **15** 1119 - 1150 (2006); Corda C - *Response of laser interferometers to scalar gravitational waves*- talk in the *Gravitational Waves Data Analysis Workshop in the General Relativity Trimester of the Institut Henri Poincare* - Paris 13-17 November 2006, on the web in www.luth2.obspm.fr/IHP06/workshops/gwdata/corda.pdf
- [13] Baskaran D and Grishchuk LP - Class. Quant. Grav. **21** 4041-4061 (2004)

- [14] Misner CW, Thorne KS and Wheeler JA - “Gravitation” - W.H. Feeman and Company - 1973
- [15] Rakhmanov M - Phys. Rev. D **71** 084003 (2005)
- [16] Landau L and Lifshits E - “Teoria dei campi” - Editori riuniti edition III (1999)
- [17] Maggiore M - Physics Reports **331**, 283-367 (2000)
- [18] Grishchuk LP - Sov. Phys. Usp. **20** 319 (1977)
- [19] Saulson P - *Fundamental of Interferometric Gravitational Waves Detectors* - World Scientific, Singapore (1994)
- [20] Estabrook FB and Wahlquist HD - Gen. Relativ. Gravit. **6** 439 (1975)
- [21] Thorne KS - *300 Years of Gravitation* - Ed. Hawking SW and Israel W Cambridge University Press p. 330 (1987)
- [22] Estabrook FB - Gen. Relativ. Gravit. **17** 719 (1975)